

# REM2

## Remote Control with Backlit Buttons



### Description

The REM2 is a water-resistant, five-button remote control that provides the user with the status of their system by pressing the [ i ] button. The remote control provides both auditory and visual feedback in an attractive streamlined style.

The REM1 is constructed with solid, stylish black plastic, with a red backlight behind the buttons. The REM2 is available in 433MHz or 868MHz.

### Features

- System status memory
- Five backlit buttons
- Performs up to 6 different actions
- Water resistant
- Available in 433Mhz or 868Mhz
- Easily replaceable battery
- Typical wireless range from 30m to 45m

# REM2 Overview



## System Status Memory

The REM2 will keep the last system status received from the control panel in memory. Momentarily press the Info button to display the last system status, even when out of range. This is used to confirm the last action you did on the system.

## Water Resistant

The REM2's water resistant casing ensures that the REM2 is protected against accidental splashes or rain.

## Replaceable battery

Simply remove the screw and the back cover and replace with a new 3V lithium battery (CR2032).

## Backlit Buttons

All buttons are backlit so are easily seen in the dark, and the remote also features a red LED near the top so that it is easy to tell that the button push has been transmitted.

## Compatibility

### Consoles/Control Panels

- Magellan All-In-One Wireless Console (MG6130 / MG6160)
- 32-Zones Wireless Transceiver Control Panel (MG5000 / MG5050)

### Wireless Expansion Modules

- Magellan Wireless Expansion Module (RTX3)

## Specifications

<b>Battery</b>	One 3V lithium battery (CR2032)
<b>Range</b>	30m with the MG6130 and MG6160
	45m with the MG5000 and MG5050
	45m with the RTX3